

Remote Power Manager: RPM-3011-N

Features

Installed in Rack	Horizontal
Power Monitor	Meter, Web, SNMP, Free Bundle Software
Power Control	Web, SNMP, API, Telephone, Manual
Power Action	Power on Sequential. Safe shutdown. Safe Reboot
Daisy Chain	Up to 15 units.
Event Alert	Email, Trap
Co-operate Device	Temp./Humidity Probe, UPS.
Protection	Circuit Breaker
OS Safe Shutdown	Windows, Linux
Includes	Mounting Bracket

Specification

Hardware	
iLink Interface	2 x RJ11, Connect to UPS, RPM up to 15 RPM client
NT Safe Shutdown	8 x RJ11
Power Control	1 x Master ; 8 x Switch for each outlet
Output	6 x NEMA 5-15R
	2 x L5-30R
Input	1 x L5-30P
Power Protection	30Amp Circuit Breaker
LED Indicator	
On/Off Status	8 Red LEDs for 8 outlets
Control Mode	8 Green LEDs for internet/non internet control
ID of iLink Cascade	16 Yellow LEDs to indicate the ID of iLink cascade
Operation	
Nominal Input Voltage	110V
Input Voltage Range	85-165V
Frequency	50/60HZ full range
Maximum Output Capacity	30Amp
Operating Temperature	0 TO 40 degree C
Relative Humidity	0 - 95% non-condensing
Size L x W x H	88 x 431.5 x 162.5 mm
	5.5 kg
	UL, FCC