

# Remote Power Manager: RPM-1522-N

## Features

<b>Installed in Rack</b>	Horizontal
<b>Power Monitor</b>	Meter, Web, SNMP, Free Bundle Software
<b>Power Control</b>	Web, SNMP, API, Telephone, Manual
<b>Power Action</b>	Power on Sequential. Safe shutdown. Safe Reboot
<b>Daisy Chain</b>	Up to 15 units.
<b>Event Alert</b>	Email, Trap
<b>Co-operate Device</b>	Temp./Humidity Probe, UPS.
<b>Protection</b>	Circuit Breaker
<b>OS Safe Shutdown</b>	Windows, Linux
<b>Includes</b>	Mounting Bracket

## Specification

<b>Hardware</b>	
iLink Interface	2 x RJ11, Connect to UPS, RPM up to 15 RPM client
NT Safe Shutdown	8 x RJ11
Power Control	1 x Master ; 8 x Switch for each outlet
Output	8 x IEC320 C13
Input	1 x IEC320 C14
Power Protection	7Amp Circuit Breaker
<b>LED Indicator</b>	
On/Off Status	8 Red LEDs for 8 outlets
Control Mode	8 Green LEDs for internet/non internet control
ID of iLink Cascade	16 Yellow LEDs to indicate the ID of iLink cascade
<b>Operation</b>	
Nominal Input Voltage	230V
Input Voltage Range	160-320V
Frequency	50/60HZ full range
Maximum Output Capacity	7Amp
Operating Temperature	0 TO 40 degree C
Relative Humidity	0 - 95% non-condensing
Size L x W x H	44 x 431.5 x 162.5 mm 2.5 kg UL, FCC