

Remote Power Manager: RPM-3022-MNP

Features

Installed in Rack	Horizontal
Power Monitor	Meter, Web, SNMP, Free Bundle Software
Power Control	Web, SNMP, API, Telephone, Manual
Power Action	Power on Sequential. Safe shutdown. Safe Reboot
Daisy Chain	Up to 15 units.
Event Alert	Email, Trap
Co-operate Device	Temp./Humidity Probe, UPS.
Protection	Circuit Breaker
OS Safe Shutdown	Windows, Linux
Includes	Mounting Bracket

Specification

SNMP Card	
LAN Interface	1 x RJ45 ; 10/100M Auto Detect
ENV	1 x RJ11
Reset Key	1 x Button
Hardware	
iLink Interface	2 x RJ11, Connect to UPS, RPM up to 15 RPM client
NT Safe Shutdown	8 x RJ11
Power Control	1 x Master ; 8 x Switch for each outlet
Output	6 x IEC320 C13
	2 x IEC320 C19
Input	1 x IEC320 C20
Power Protection	16 Amp Circuit Breaker
LED Indicator	
On/Off Status	8 Red LEDs for 8 outlets
Control Mode	8 Green LEDs for internet/non internet control
ID of iLink Cascade	16 Yellow LEDs to indicate the ID of iLink cascade
Operation	
Nominal Input Voltage	230V
Input Voltage Range	165-320V
Frequency	50/60HZ full range
Maximum Output Capacity	16 Amp
Operating Temperature	0 TO 40 degree C
Relative Humidity	0 - 95% non-condensing
Size L x W x H	88 x 431.5 x 162.5 mm
	5.5 kg
	UL, FCC