

Switched PDU: AMz-1023/SW-08-1

Features

Current Meter	Digital True RMS Current Meter
Installed in Rack	Vertical
Remote Power Monitor	Web, SNMP, Free Bundle Software
Audible Alarm	2 Phase, Warning and Overload
Event Alert	Email, Trap, Audible Alarm
Protection	Circuit Breaker
Includes	Mounting Bracket

Specification

General	
Output	(8) IEC 320 C13
Input	(1) IEC 320 C14 attached power cord, 3 meters long
Protection	(1) 10 AMP Circuit Breaker
Communication	
IP Address	(1) Yellow LED
PDU Status	(1) Green LED
Power Status	(8) Red LED
Power Monitor	(1) RJ45 for Ethernet
Current	3 Digits Meter Range: 0A ~ 20A Resolution: 0.1A Precision: $\pm 2\% \pm 0.1\text{AMP}$
Operation	
Input Voltage	230V
Output Range	160-320V
Frequency	50/60HZ full range
Max. Output Current	10 Amp
Temperature	0 ~ 40 Celsius degree
Humidity	0% ~ 90%
Size	38 x 583 x 56 mm
Weight	2 kg