

Monitored PDU: AMz-2011-08-1

Features

Current Meter	Digital True RMS Current Meter
Installed in Rack	Vertical
Remote Power Monitor	Web, SNMP, Free Bundle Software
Audible Alarm	2 Phase, Warning and Overload
Event Alert	Email, Trap, Audible Alarm
Protection	Circuit Breaker
Includes	Mounting Bracket

Specification

General	
Output	(8) NEMA 5-15R
Input	(1) NEMA 5-15P attached power cord, 3 meters long
Protection	(1) 20 AMP Circuit Breaker
Communication	
IP Address	(1) Yellow LED
PDU Status	(1) Green LED
Power Monitor	(1) RJ45 for Ethernet
Current	3 Digits Meter Range: 0A ~ 20A Resolution: 0.1A Precision: $\pm 2\% \pm 0.1\text{AMP}$
Operation	
Input Voltage	110V
Output Range	85-165V
Frequency	50/60HZ full range
Max. Output Current	20 Amp
Temperature	0 ~ 40 Celsius degree
Humidity	0% ~ 90%
Size	38 x 533 x 44 mm
Weight	2.5 kg